

06/01/00

Please type a plus sign (+) inside this box → ☒

PTO/SB/05 (4/98)

Approved for use through 09/30/2000. OMB 0851-0032

Patent and Trademark Office; U.S. DEPARTMENT OF COMMERCE
Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.**UTILITY
PATENT APPLICATION
TRANSMITTAL**

(Only for new nonprovisional applications under 37 C.F.R. § 1.53(b))

Attorney Docket No.	P-1518-US
First Inventor or Application Identifier	DAVIDSON, Jeffrey
Title	VARIABLE RATE CONTINUOUS MODE SATELLITE MODEM
Express Mail Label No.	

APPLICATION ELEMENTS
See MPEP chapter 600 concerning patent application contents**ADDRESS TO:** Assistant Commissioner for Patents
Box Patent Application
Washington, DC 20231

1. ☒ * Fee Transmittal Form (e.g., PTO/SB/17)
(Submit an original and a duplicate for fee processing)
2. ☒ Specification [Total Pages 39]
(preferred arrangement set forth below)
- Descriptive title of the invention
 - Cross References to Related Applications
 - Reference to Microfiche Appendix
 - Background of the invention
 - Brief Summary of the invention
 - Brief Description of the Drawings (if filed)
 - Detailed Description
 - Claim(s)
 - Abstract of the Disclosure
3. ☒ Drawing(s) (35 U.S.C. 113) [Total Sheets 15]
4. Oath or Declaration [Total Pages 4]
- a. ☒ Newly executed (original or copy)
- b. ☐ Copy from a prior application (37 C.F.R. § 1.63(d))
(for continuation/divisional with Box 16 completed)
- i. ☐ **DELETION OF INVENTOR(S)**
Signed statement attached deleting
inventor(s) named in the prior application,
see 37 C.F.R. §§ 1.63(d)(2) and 1.33(b).

5. ☐ Microfiche Computer Program (Appendix)
6. Nucleotide and/or Amino Acid Sequence Submission
(if applicable, all necessary)
- a. ☐ Computer Readable Copy
- b. ☐ Paper Copy (identical to computer copy)
- c. ☐ Statement verifying identity of above copies

ACCOMPANYING APPLICATION PARTS

7. ☒ Assignment Papers (cover sheet & document(s))
8. ☐ 37 C.F.R. §3.73(b) Statement (when there is an assignee) ☐ Power of Attorney
9. ☐ English Translation Document (if applicable)
10. ☐ Information Disclosure Statement(IDS)/PTO-1449 ☐ Copies of IDS Citations
11. ☐ Preliminary Amendment
12. ☐ Return Receipt Postcard (MPEP 5303)
(Should be specifically itemized)
13. ☒ * Small Entity Statement(s) ☐ Statement filed in prior application, Status still proper and desired (PTO/SB/09-12)
14. ☐ Certified Copy of Priority Document(s)
(if foreign priority is claimed)
15. ☒ Other: postcard

NOTE FOR ITEMS 1 & 13: IN ORDER TO BE ENTITLED TO PAY SMALL ENTITY FEES, A SMALL ENTITY STATEMENT IS REQUIRED (37 C.F.R. § 1.27) EXCEPT IF ONE FILED IN A PRIOR APPLICATION IS RELIED UPON (37 C.F.R. § 1.28)

16. If a CONTINUING APPLICATION, check appropriate box, and supply the requisite information below and in a preliminary amendment:
☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP)

of prior application No.: _____ / _____


Prior application information: Examiner _____

Group/Art Unit: _____

For CONTINUATION or DIVISIONAL APPS only: The entire disclosure of the prior application, from which an oath or declaration is supplied under Box 4b, is considered a part of the disclosure of the accompanying continuation or divisional application and is hereby incorporated by reference. The incorporation can only be relied upon when a portion has been inadvertently omitted from the submitted application parts.

17. CORRESPONDENCE ADDRESS☐ Customer Number or Bar Codeor ☒ Correspondence address below

Name	Eltan, Pearl, Latzer & Cohen-Zedek				
Address	One Crystal Park, Suite 210, 2011 Crystal Drive				
City	Arlington	State	VA	Zip Code	22202-3709
Country	USA	Telephone	(703) 496-0800	Fax	(703) 496-0800

Name (Print/Type)	Mark S. Cohen	Registration No. (Attorney/Agent)	42,425
Signature		Date	1 June 2000

Burden Hour Statement: This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231.

PTO
09/584746
06/01/00

STATEMENT CLAIMING SMALL ENTITY STATUS
(37 CFR 1.9(f) & 1.27(c))--SMALL BUSINESS CONCERN

Docket Number (Optional)

P-1518-US

Applicant, Patentee, or Identifier: DAVIDSON, Jeffrey et al.

Application or Patent No.: _____

Filed or Issued: _____

Title: VARIABLE RATE CONTINUOUS MODE SATELLITE MODEM

I hereby state that I am

☐ the owner of the small business concern identified below:

☒ an official of the small business concern empowered to act on behalf of the concern identified below:

NAME OF SMALL BUSINESS CONCERN SHIRON SATELLITE COMMUNICATIONS(1996) LTD.

ADDRESS OF SMALL BUSINESS CONCERN 23 Hasiyim Street, Kiryat Matalon, Petach Tikva 48170, Israel.

I hereby state that the above identified small business concern qualifies as a small business concern as defined in 13 CFR Part 121 for purposes of paying reduced fees to the United States Patent and Trademark Office. Questions related to size standards for a small business concern may be directed to: Small Business Administration, Size Standards Staff, 409 Third Street, SW, Washington, DC 20416.

I hereby state that rights under contract or law have been conveyed to and remain with the small business concern identified above with regard to the invention described in:

- ☒ the specification filed herewith with title as listed above.
☐ the application identified above.
☐ the patent identified above.

If the rights held by the above identified small business concern are not exclusive, each individual, concern, or organization having rights in the invention must file separate statements as to their status as small entities, and no rights to the invention are held by any person, other than the inventor, who would not qualify as an independent inventor under 37 CFR 1.9(c) if that person made the invention, or by any concern which would not qualify as a small business concern under 37 CFR 1.9(d), or a nonprofit organization under 37 CFR 1.9(e).

Each person, concern, or organization having any rights in the invention is listed below:

- ☒ no such person, concern, or organization exists.
☐ each such person, concern, or organization is listed below.

Separate statements are required from each named person, concern, or organization having rights to the invention stating their status as small entities. (37 CFR 1.27)

I acknowledge the duty to file, in this application or patent, notification of any change in status resulting in loss or entitlement to small entity status prior to paying, or at the time of paying, the earliest of the issue fee or any maintenance fee due after the date on which status as a small entity is no longer appropriate. (37 CFR 1.28(b))

NAME OF PERSON SIGNING X ARIE REICHMAN

TITLE OF PERSON IF OTHER THAN OWNER X CTO

ADDRESS OF PERSON SIGNING X BAR ILAN 3 KPAR SABA

SIGNATURE X Arie Reichman DATE X 11 May 2000

Business Hour Statement: This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Washington, DC 20231.

VARIABLE RATE CONTINUOUS MODE SATELLITE MODEM

FIELD OF THE INVENTION

The present invention relates generally to communications and more particularly relates to a variable rate continuous mode modem suitable for satellite communications.

5

BACKGROUND OF THE INVENTION

10 Recently there has been a widespread proliferation of satellite communications systems throughout the world. A large number of consumers have acquired satellite communications equipment for home reception of satellite broadcast television signals in addition to many businesses having acquired such equipment for the purpose of receiving and/or transmitting useful business information.

15 Typically, satellite communications systems have been constructed using a combination of RF circuitry, IF and baseband circuitry. A common trend in the art is to implement the IF and baseband modules using one or more FPGAs and/or ASICs. A disadvantage of this is that it is difficult or even impossible to perform some techniques that are only possible to perform in software. Attempting to perform these techniques in circuitry, if possible, would result in large, complex and expensive silicon.

Thus it is desirable to have a satellite modem wherein the receiver portion is mainly implemented in software so as to reduce cost, making necessary changes much simpler to perform and potentially reducing the size of the receiver.

SUMMARY OF THE INVENTION

5 The present invention overcomes the disadvantages of the prior art by providing a satellite modem whose baseband modules can be implemented mostly in software running on a suitable processor such as a high speed digital signal processor (DSP) which are commonly available today. The modem includes a RF portion and a baseband portion. The digitized output of a matched filter is input to the baseband processing portion that consists of software executing on a DSP.

10 The modem comprises an antenna coupled to an upconverter/downconverter. The upconverter/downconverter is coupled to a RF transceiver which functions to receive a transmit signal from a baseband transmitter module and generate a signal for input to the upconverter/downconverter. The RF transceiver also functions to receive a downconverted signal and output an IF signal for input to an IF module. The IF functions to generate I and Q outputs that are input to a digital baseband module. The baseband module can be implemented as software executing on a DSP.

15 A novel aspect of the present invention is the method of performing phase acquisition. In particular, the invention disclosed a technique of modulation wipe off wherein the effects of modulation are removed. The technique involves rotating all the symbol vectors into a single quadrant. This is done in order to avoid the case where the constellation points are spread over more than one quadrant due to excessive noise being present in the channel.

20 Another novel aspect of the invention is the signal detection technique. The signal detection technique performs signal detection and frequency acquisition in the presence of multiple signals in accordance with a method described hereinbelow.

25 Still another novel aspect of the present invention is the timing acquisition technique that includes an unwrapping technique. This functions to correct timing errors before averaging is performed. In addition, linear changes to the time estimates are performed using LSR techniques.

30 The satellite modem of the present invention, wherein the baseband receiver and transmitter are mainly implemented in software, provides for a reduction in cost, makes performing necessary changes much simpler and reduces the size of the modem. In addition, the invention represents a significant step toward the goal of a complete software radio.

There is thus provided in accordance with the present invention a satellite modem, comprising a housing, a antenna for receiving and transmitting radio frequency (RF) signals, an upconverter/downconverter coupled to the antenna and adapted to upconvert RF signals

from a first frequency band to a second frequency band, and adapted to downconvert RF signals from the second frequency band to the first frequency band, an RF transceiver coupled to the upconverter/downconverter and adapted to receive an output transmit signal and to generate an output RF signal therefrom, the RF transceiver adapted to receive an input RF signal from the upconverter/downconverter and generate an input receive signal therefrom, an intermediate frequency (IF) module adapted to receive the input receive signal and generate I and Q signals in response thereto, a baseband module adapted to receive the I and Q signals and to generate receive data in accordance therewith and a baseband module adapted to generate the output transmit signal in accordance with a transmit data signal input thereto.

There is also provided in accordance with the present invention a receiver baseband apparatus, comprising input means adapted to receive an I and Q signal, an I matched filter adapted to receive the I signal and generate an I filtered output therefrom, a Q matched filter adapted to receive the Q signal and generate a Q filtered output therefrom, a processor programmed to perform automatic gain control (AGC) and generate an AG control signal therefrom, perform timing detection and generate an A/D clock control signal therefrom, perform phase detection and generate a voltage controlled oscillator (VCO) control signal therefrom, a decoder adapted to receive the I output signal and the Q output signal from the processor and to generate a decoded output therefrom, a deinterleaver adapted to generate a deinterleaved output in accordance with the decoded output signal input thereto, a forward error correction decoder adapted to generate output receive data in accordance with the deinterleaved output signal input thereto and a controller adapted to manage and control the input means, I matched filter, Q matched filter, the processor, the decoder, the deinterleaver and the forward error correction decoder.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention is herein described, by way of example only, with reference to the accompanying drawings, wherein:

Fig. 1 is a block diagram illustrating the RF, IF and baseband portions of the variable rate satellite modem of the present invention;

Fig. 2 is a block diagram illustrating the baseband module portion of the variable rate satellite modem in more detail;

Fig. 3 is a flow diagram illustrating the main software processing loop of the variable rate modem;

Fig. 4 is a flow diagram illustrating the processing performed upon power up or after the communication link is broken;

Fig. 5 is a flow diagram illustrating the initial automatic gain control processing portion of the variable rate modem;

Fig. 6 is a chart illustrating the results of correlation between the spectral estimation and the spectral mask of the expected signal with both desired and adjacent signals having bit rates equal to 9600 bps;

Fig. 7 is a chart illustrating the correlation result with the desired signal having a bit rate equal to 9600 bps and an interfering signal having a bit rate of 128 Kbps;

Fig. 8 is a flow diagram illustrating the signal detect and frequency acquisition processing portion performed upon power up;

Fig. 9 is a flow diagram illustrating the timing, AGC, frequency and phase acquisition processing portion of the variable rate modem;

Fig. 10 is a flow diagram illustrating the fine frequency estimation processing portion of the variable rate modem;

Fig. 11 is a flow diagram illustrating the coarse phase acquisition processing portion of the variable rate modem;

Fig. 12 is a flow diagram illustrating the fine phase acquisition processing portion of the variable rate modem;

Fig. 13 is a block diagram illustrating tracking portion of the variable rate modem;

Fig. 14 is a flow diagram illustrating the pre-track processing portion of the variable rate modem;

Fig. 15 is a flow diagram illustrating the AGC tracking portion of the variable rate modem;

Fig. 16 is a block diagram illustrating a model of the timing tracking portion of the variable rate modem;

Fig. 17 is a block diagram illustrating the phase tracking portion of the variable rate modem; and

5 Fig. 18 is a flow diagram illustrating the tracking processing portion of the variable rate modem.

007090" 94248550

DETAILED DESCRIPTION OF THE INVENTION

Notation Used Throughout

The following notation is used throughout this document.

Term	Definition
AGC	Automatic Gain Control
ASIC	Application Specific Integrate Circuit
BER	Bit Error Rate
DDS	Direct Digital Synthesizer
DEC	Circular Drift Function of EC
DFT	Discrete Frequency Transform
DSP	Digital Signal Processor
ES	Estimated Spectrum
FE	Frequency Estimate
FFT	Fast Fourier Transform
FIR	Finite Impulse Response
FPGA	Field Programmable Gate Array
IF	Intermediate Frequency
IIR	Infinite Impulse Response
LIM	Limit of Uncertainty Range
LPF	Low Pass Filter
LSR	Least Squares Regression
NCO	Numerically Controlled Oscillator
NFFT	Number of FFT points
PI	Peak Indexes
PLL	Phase Lock Loop
QPSK	Quadrature Phase Shift Keying
RF	Radio Frequency
RMS	Root Mean Square
SNR	Signal to Noise Ratio
TS	Theoretic Spectrum Mask
VCO	Voltage Controlled Oscillator

5

General Description

The present invention is a variable rate continuous mode satellite modem capable of transmitting and receiving at a symbol rate in the range of 9.6 K to 256 K symbols/sec. Note that the bit rate depends on the coding rate. For example, at a code rate of $\frac{1}{2}$, with QPSK, the bit rate is equal to the symbol rate. At a code rate of $\frac{3}{4}$, with QPSK, the bit rate is 50% more than the symbol rate. To aid in understanding the principles of the present invention, the description of the processing performed in the modem is divided into five main portions: (1) the main loop including a state machine for defining acquisition, tracking, etc., (2) signal detection and initial frequency estimation, (3) acquisition of timing, frequency and phase, (4)

pre-tracking (AGC, timing and phase tracking) with a phase loop having a larger bandwidth and phase ambiguity to be solved and (5) tracking of the AGC, timing and phase. Additional processing includes the soft decision data detection.

The main loop will now be described in more detail. A block diagram illustrating the RF, IF and baseband portions of the variable rate satellite modem of the present invention is shown in Figure 1. The modem, generally referenced 10, comprises a housing (not shown), an upconverter/downconverter 13 coupled to an external antenna 12 and a RF transceiver 14 coupled to the upconverter/downconverter 13. The upconverter functions to convert the output of the RF transceiver 14, e.g., L band, to the RF output frequency, e.g., C or Ku band. The downconverter performs downconversion of the signal received over the antenna from RF frequencies, e.g., C or Ku band, to L band for input to the RF transceiver 14. The RF transceiver downconverts the received RF signal to an IF signal. The IF signal output of the RF transceiver 14 is input to the IF module 16 which functions to generate the I and Q baseband signals. The baseband module 18 demodulates the I and Q signals to yield the receive Rx data. The baseband module 18 performs signal processing tasks on the I and Q data from the IF module 16 such as Viterbi decoding, de-interleaving and Reed Solomon decoding

In the transmit direction, the baseband transmitter 20 generates a baseband transmit signal in response to the input transmit Tx data. The baseband transmit signal is input to the RF transceiver 14 which upconverts the signal to an RF frequency signal which is then input to the external antenna 12.

Baseband Module

A block diagram illustrating the baseband module portion of the variable rate satellite modem in more detail is shown in Figure 2. The baseband module 18 receives the baseband I and Q signals. The analog I signal is converted to digital by A/D converter 21. The 8-bit digitized I signal is input to a matched filter 23. The analog Q signal is converted to digital by A/D converter 22. The 8-bit digitized Q signal is input to a matched filter 24. The matched filters 23, 24 are implemented in hardware but may alternatively be implemented in software. The I and Q outputs of the matched filters 23, 24 are input to processor 25.

In one embodiment of the invention, for example, the RF receive frequency for C band operation is approximately 4 GHz and the RF transmit frequency is approximately 6 GHz. The RF transceiver 14 downconverts/upconverts to/from an IF frequency of approximately 900 MHz. The IF module 16 downconverts the IF signal to analog I and Q

baseband signals within the bandwidth range of approximately 0 to 170 KHz. The baseband module 18 demodulates the baseband I and Q signal to a soft decision digital data signal. Note that the IF frequency, between the RF transceiver 14 and the IF module 16, may be 70 MHz \pm 18 MHz or 140 MHz \pm 36 MHz. The RF transceiver 14 may comprise a commercially available transceiver suitable for operation with the satellite modem of the present invention. For Ku band operation, the RF receive frequency is approximately 12 GHz and the RF transmit frequency is approximately 14 GHz. The RF transceiver downconverts/upconverts to/from an IF frequency within the range of approximately 950 to 1450 MHz.

In an alternative embodiment, the signal from the RF transceiver constitutes a first IF which is input to a modified IF module that outputs a second IF signal. This second IF signal is converted to digital via an A/D converter and input to a digital converter that functions to generate I and Q signals.

The processor 25 performs the majority of the signal processing functions in the modem 10 such as activity detection, timing acquisition, frequency acquisition, phase acquisition and tracking. The processor 25 functions to output 3-bit I and Q signals that are input to a Viterbi decoder 26. The output of the Viterbi decoder 26 is input to a deinterleaver 27. The output of the deinterleaver 27 is input to a Reed Solomon decoder 28 which functions to output the receive Rx data.

A controller 29 controls and manages the operation of the baseband module and clock circuitry 31 functions to provide the various clocks needed by the elements of the baseband module 18.

Main Processing Loop

A flow diagram illustrating the main software processing loop of the variable rate modem is shown in Figure 3. Upon power up (step 32) a series of start up tasks are performed. These include activity detection (step 34), acquisition (step 36) and pre-tracking (step 37). The activity detection (step 34) performs signal detection, AGC and coarse frequency acquisition. In this step, the modem is listening for a signal from the transmitter. The frequency/tuning offset is reduced to a suitable level such that when the PLL is started, the errors are relatively small and the PLL is capable of locking onto the signal. During the activity detect phase, no matched filtering is performed. In addition, the frequency is variable with an approximately frequency offset of 30 KHz at a low rate and with a bandwidth of approximately 7 to 8 KHz.

During acquisition (step 36), AGC is performed as well as timing, fine frequency and phase acquisition. Next, during the pre-tracking phase (step 37), phase tracking acquisition is performed wherein a phase estimate is performed every four symbols.

Once the start up phase is completed, tracking is performed (step 38). This step includes AGC, timing and phase tracking. The above steps are repeated when tracking is lost on the signal or after each time the modem is powered up.

Activity Detection

Each of the above steps is described in more detail hereinbelow beginning with the activity detection phase. A flow diagram illustrating the activity detect method (step 34 Figure 3) is shown in Figure 4. The following steps are performed upon power up or after a catastrophic event whereby the communication link is completely broken. The initial automatic gain control (AGC) step includes measuring the energy at the output of the A/D converters 21,22 (Figure 2), i.e., at the input buffer (step 40).

Next, the decimation of the input signal is performed (step 42). Decimation by a factor of 1, 2, 4 or 8 is performed. Signal detection and initial coarse frequency acquisition and estimation is performed (step 44). If signal activity is not detected, the method loops back and repeats steps 40, 42, 44 until a signal is detected (step 46).

Each of the steps of the activity detection method will now be described in more detail beginning with the initial AGC step 40. A flow diagram illustrating the initial automatic gain control (AGC) processing portion of the variable rate modem is shown in Figure 5. First, N samples of the input signal are collected whereby N may be 64, 128 or 256 (step 50). The unfiltered samples are expressed as

$$z_n = I_n + jQ_n \quad (1)$$

The mean square energy E_{ms} is then calculated using the following equation (step 51).

$$E_{ms} = \frac{1}{N} \sum_{i=1}^N |z_i|^2 \quad (2)$$

where G_0 is the gain of the AGC and IG_0 is the inverse gain. The inverse gain IG_0 is set equal to $256 * E_{ms}$ for scaling the RMS of the A/D converter input at 1/16 maximum input voltage level (step 52). The value of G_0 is determined from a lookup table (step 54). The G_0 value is then written to the AGC hardware (step 56). Signal detection is then performed (step 58).

Signal decimation (step 42 Figure 4) is performed before the actual processing in order to improve the frequency resolution at lower data rates. The resolution achieved is a

particular fraction of the symbol rate. It is preferable to have between 4 and 10 samples per symbol, except for the case of very low data rates. This means that the signal is relatively wideband in the normalized frequency domain thereby enabling a reasonable resolution without requiring very long FFTs. The resolution can be expressed as

$$\begin{aligned} \frac{\text{binwidth}}{\text{Symbol Rate}} &= \frac{f_s / N}{R_b} \\ &= \frac{f_s}{R_b} \cdot \frac{1}{N} \\ &= \frac{nss}{N} \end{aligned} \quad (3)$$

where

f_s is the sampling rate

R_b is the symbol rate

nss is the number of samples per symbol

N is the number of points in the FFT

The parameters of the decimation for activity detection, also referred to as gear shifting, is presented below in Table 1.

Table 1

Symbol Rate (KHz)	Sample Rate at A/D (KHz)	Max BW (KHz)	Decimation Factor	Number of samples per symbol	Normalized Cutoff Frequency	Relative Resolution (%)
9.6 - 12	768	38.1	8	8 - 10	0.0496	3.1 - 3.9
12 - 16	864	41	8	6.75 - 9	0.0475	2.63 - 3.5
16 - 24	928	46.2	8	4.83 - 7.25	0.04978	1.88 - 2.8
24 - 32	512	51.6	4	4 - 5.33	0.1008	1.5 - 2
32 - 64	512-1024	51.6	4	4	0.1008	1.5
64 - 128	512-1024	73.2	2	4	0.1430	1.5
128 - 256	512-1024	116.4	1	4	0.2273	1.5

The maximum bandwidth is determined by the bandwidth of the higher rate plus a maximum frequency offset of 30 KHz.

The relative required resolution is determined from the limitations of the phase acquisition algorithm. The phase acquisition algorithm operates on blocks of eight symbols, trying four hypotheses for the axis, each rotated by 22.5 degrees from one another.

Therefore, over eight symbols, the maximum frequency offset causes less than 10 to 20% of 22.5 degrees, i.e., less than 2.5 to 5 degrees phase shift. This implies a resolution of much less than one degree per symbol. This corresponds to a resolution of less than 0.3% of

the symbol period. This resolution, however, is very difficult to obtain, thus a fine frequency acquisition is performed prior to the phase acquisition. This yields resolutions between 1.5 to 3% of the symbol period.

5 The decimation is performed by filtering utilizing half band filters, which results in decimation by a factor of two. In addition, these filters are relatively inexpensive to implement since (1) approximately half the coefficients are zero, (2) the filter order is relatively low due to a wide transition band between the pass and stop band and (3) only every second output need be computed due to the decimation by two. The design of half band filters is described in more detail in "Multirate Systems and Filter Banks," P.P. 10 Vaidyanathan, Prentice Hall 1993; "A Trick for the Design of FIR Half Band Filters," P.P. Vaidyanathan and T. Nguyen, IEEE Transactions on Circuits and Systems, Vol. CAS-34, pp. 378-389, April 1989, both of which are incorporated herein by reference.

15 In the embodiment presented herein, a filter having a length of 9 for the first stage is sufficient, while a filter length between 11 and 13 is sufficient for the second stage (or the single stage when decimation by 2 is performed).

The coefficients for the filters are presented below in Tables 2 through 4.

Table 2: Coefficients For Decimation By Factor Of 8 Using Three Filters

Filter #1						
-0.0336	0	0.2835	0.5000	0.2835	0	-0.0336
Filter #2						
-0.0422	0	0.2902	0.5000	0.2902	0	-0.0422
Filter #3: Columns 1 through 7						
0.0131	0	-0.0236	0	0.0463	0	-0.0949
Filter #3: Columns 8 through 14						
0	0.3144	0.5000	0.3144	0	-0.0949	0
Filter #3: Columns 15 through 19						
0.0463	0	-0.0236	0	0.0131		

5

Table 3: Coefficients For Decimation By Factor Of 4 Using Two Filters

Filter #1						
-0.0426	0	0.2904	0.5000	0.2904	0	-0.0426
Filter #2: Columns 1 through 7						
0.0146	0	-0.0246	0	0.0472	0	-0.0956
Filter #2: Columns 8 through 14						
0	0.3147	0.5000	0.3147	0	-0.0956	0
Filter #2: Columns 15 through 19						
0.0472	0	-0.0246	0	0.0146		

Table 4: Coefficients For Decimation By Factor Of 2 Using One Filter

Filter #3: Columns 1 through 7						
0.0169	0	-0.0691	0	0.3041	0.5000	0.3041
Filter #3: Columns 8 through 11						
0	-0.0691	0	0.0169			

10

007090" 94248560

Signal Detection and Frequency Acquisition

This section describes the method used by the variable rate modem for signal detection and frequency acquisition in the presence of multiple signals in the spectrum. According to Intelsat standards, two signals can be placed at frequencies that are a distance of 5 $0.7 * (\text{symbol_rate}_1 + \text{symbol_rate}_2)$ as measured from center frequency to center frequency and whereby the $\frac{E_b}{N_0}$ levels differ by at most 7 dB.

The methods of the present invention utilize FFT periodograms for spectral estimation followed by cyclic correlation with the spectral mask of the expected signal in order to detect the center of the signal. Figures 6 and 7 are charts illustrating the results of correlation 10 between the spectral estimation and the spectral mask of the expected signal. The result of the correlation for the Intelsat scenario, for example, is shown in Figures 6 and 7. In both figures, the expected signal has a power level lower by 7 dB than adjacent signals and has a data rate of 9600 bps.

With reference to Figures 6 and 7, multiple peaks can be detected in the correlation. 15 In contrast to the single signal scenario, the maximal peak is not the sole candidate for the central frequency of the expected signal. Preferably, peaks in the correlation should be examined to determine the potential locations of the desired signal.

Spectrum Estimation

A flow diagram illustrating the signal detect and frequency acquisition processing 20 portion (step 44 Figure 4) performed upon power up is shown in Figure 8. The first step performed is to calculate the spectrum of the received signal (step 60). The estimated spectrum (ES) is represented as an array or size 256. The following pseudo code describes this step.

Spectral Estimation Pseudo Code

25 1. reset the ES array to zero;
2. for j=0 to num_reps - 1 (num_reps = 32 for low $\frac{E_b}{N_0}$ levels and 16 for regular operation)
 get \bar{z} , a vector of 256 received signal samples, $z_i = I_i + jQ_i, i = 0..255$
 $ES = ES + |FFT(\bar{z})|^2$
30 endfor
3. calculate $ES = \frac{ES}{\text{num_reps}}$;

4. FFT shift ES:

$$ES'(i) = \begin{cases} ES(i-128), i = 128 + 255 \\ ES(i+128), i = 0 + 127 \end{cases}, \text{ where } ES' \text{ is the FFT shifted version of } ES,$$

throughout the remainder of this section, however, ES' is denoted as ES ;

5. remove DC using:

$$ES(128) = \frac{ES(127) + ES(129)}{2};$$

Signal Presence Determination

Next, the presence of a signal is determined using the following pseudo code (step 62).

Signal Presence Determination Pseudo Code

1. smooth the Estimated Spectrum using an 11 coefficient low pass filter (LPF) presented below in Table 5;

$$ESS(i) = \sum_{j=-5}^5 ES(i-j)h(j), i = 0 + 255$$

where $ES(i) = 0$ for $i < 0$ and $i > 255$;

Table 5: Coefficients For Low Pass Filter

h_{-5}	h_{-4}	h_{-3}	h_{-2}	h_{-1}	h_0	h_1	h_2	h_3	h_4	h_5
0.010	0.0249	0.0668	0.1249	0.1756	0.1957	0.1756	0.1249	0.0668	0.0249	0.010

2. calculate RES, the resolution of one bin in the FFT

$$RES = \frac{\text{SamplingFrequency}}{NFFT}$$

where NFFT is defined as the number of FFT points;

3. calculate chk_rng, the range of indexes to be checked in the FFT

$$chk_rng = \text{ceil}\left(\frac{\max(3 \times 10^4, 0.7 \cdot \text{symbol_rate})}{RES}\right)$$

4. calculate max_chk and min_chk

$$\max_chk = \max\{ES_s(i)\}_{i=128-chk_rng}^{128+chk_rng}$$

$$\min_chk = \min\{ES_s(i)\}_{i=128-chk_rng}^{128+chk_rng}$$

5. calculate act_ratio

$$act_ratio = \frac{\max_chk}{\min_chk}$$

If the value of act_ratio is greater than 1.75, it is determined that a signal is present (step 64). Otherwise it is determined that no signal is present.

5

Correlation Calculation

The next step is to perform a correlation calculation (step 66). The following definitions apply:

- ES: estimated spectrum
 TS: theoretic spectrum mask
 10 EC: an array of size 256 representing the correlation function between the non smoothed ES and the TS
 LIM: the limit of the range of uncertainty

The correlation is determined using the following pseudo code (step 66).

15

Correlation Determination Pseudo Code

1. calculate LIM using the following equation;

$$LIM = \text{ceil}\left(\frac{30,000 + 0.125 \cdot \text{symbol_rate}}{RES}\right)$$

2. calculate the following;

$$20 \quad EC\left(i - \left\lceil \frac{\text{length}(TS)}{2} \right\rceil\right) = \sum_{k=0}^{\text{length}(TS)-1} ES((k+i)_{\text{mod}256}) TS(k), 128 - LIM < i < 128 + LIM$$

Peak Determination

The next step is to perform a peak determination algorithm (step 68). The following definitions apply:

25

- DEC: circular difference function of EC
 PI: list of peak indexes
 N_WIN: the minimal distance between peaks

The peak determination is determined using the following pseudo code.

30

Peak Determination Pseudo Code

1. calculate DEC using the following equation;

$$DEC(i) = \begin{cases} EC(0) - EC(255), & i = 0 \\ EC(i) - EC(i-1), & i = 1..255 \end{cases}$$

35

2. find PI, for the list of indexes i which fulfill the conditions $i \in PI$

$$\begin{cases} DEC(i) \geq 0 \text{ and } DEC(i+1) < 0, i = 0..254 \\ DEC(255) \geq 0 \text{ and } DEC(0) < 0, i = 255 \end{cases}$$

3. find the value of the minimum peak and eliminate from the list those peaks that are 10 dB (0.1) smaller than the maximum peak;

4. calculate N_WIN using the following;

$$N_WIN = \begin{cases} \text{floor}\left(0.35 \frac{NFFT}{nss}\right) & \text{symbol_rate} \leq 64 \text{ KHz} \\ \text{floor}\left(0.175 \frac{NFFT}{nss}\right) & \text{symbol_rate} > 64 \text{ KHz} \end{cases}$$

5. If two or more peaks are closer than N_WIN, keep the highest between them in the list. The order of the removal is from the highest peak to the lowest. Note that it is well known that the center frequencies of two signals are separated by the sum of half the signal's bandwidth, i.e., $0.7(\text{symbol_rate}_1 + \text{symbol_rate}_2)$. In practice, since (1) the peaks of interferers are not accurately detected, (2) the peak of a small rate signal tends to get closer to the center of the high rate signal, and (3) the rate of the interferer is not known, this range should be decreased to the value given above.

Symbol Rate Calculation

The next step is to calculate the symbol rate (step 70). The following definitions apply:

BW2: one half of the bandwidth of the signal

The symbol rate is calculated utilizing the following pseudo code.

Symbol Rate Calculation Pseudo Code

1. calculate BW2 using the following;

$$BW2 = \text{ceil}\left(\frac{0.675 \cdot \text{symbol_rate}}{RES}\right)$$

2. calculate the following;

$$No_level = \text{Mean}\left(\{ES(i) | 0.85 \cdot \min_chk \leq ES(i) \leq 1.25 \cdot \min_chk, 0 \leq i \leq 255\}\right)$$

3. for $l = 1$ to the length of PI:

3.1 define Area as:

$$Area = \left\{ i \mid PI(l) - BW2 < i < PI(l) + BW2 \right\}$$

3.2 define Area2 as:

$$Area = \left\{ i \mid PI(l) - \frac{3}{8} BW2 < i < PI(l) + \frac{3}{8} BW2 \right\}$$

3.3 find max_val:

$$\max_val = \max_{k \in Area2} ES_s(k)$$

3.4 redefine the indexes of Area2 as k such that $ES_s(k) < \frac{\max_val}{2}$

$$Area2 = \left\{ i \left| PI(l) - \frac{3}{8}BW2 < i < PI(l) + \frac{3}{8}BW2, ES_s(i) < \frac{\max_val}{2} \right. \right\}$$

3.5 calculate mean_val using;

$$mean_val = \frac{\sum_{k \in Area2} ES_s(k)}{\text{number of indexes in Area2}}$$

3.6 find F_u , the smallest index in Area greater than $PI(l)$, such that $ES_s(F_u) \leq 0.5 \cdot (mean_val + No_level)$

3.7 find F_l , the highest index in Area smaller than $PI(l)$, such that $ES_s(F_l) \leq 0.5 \cdot (mean_val + No_level)$

3.8 if both F_u and F_l are found then calculate the estimated symbol rate (es_symbol_rate) corresponding to $PI(l)$ using the following:

$$es_symbol_rate = (F_u - F_l) \cdot RES$$

4. end for

5. remove from the list the peaks having es_symbol_rate higher than 1.2 times the expected symbol rate or lower than 0.75 times the expected symbol rate.

If the list of peaks is exhausted, the method continues with step 60 (step 72). If the list of peaks is not exhausted, the peak closest to the center is selected (step 74).

Frequency Acquisition

The next step is to perform frequency acquisition (step 76). The following definitions apply:

FE: the normal frequency estimation

pi: the peak index where a candidate signal is centered

The frequency acquisition is performed utilizing the following pseudo code.

Frequency Acquisition Pseudo Code

1. the normal frequency estimation (FE) is calculated using the following

$$FE = (pi - 128) \cdot RES$$

2. FE is output to the synthesizer and the central frequency is shifted in order that the frequency shift be compensated.

Communications is then attempted (step 78). If communications are not successful, the particular peak is deleted from the list and the method continues with step 72). If

communication is successful, the method terminates. Timing acquisition and fine frequency acquisition are then performed (described in more detail below).

Timing, Frequency and Phase Acquisition

A flow diagram illustrating the timing, AGC, frequency and phase acquisition processing portion (step 36 Figure 3) of the variable rate modem is shown in Figure 9. A matched filter begins operation at a normal gear shift at 4 samples per symbol (step 90). The matched filter is implemented in hardware and operate without a phase rotation. Alternatively, the matched filter can be implemented in software. The matched filter hardware controls the clocking of the A/D converters.

The normal gear shift ratios are presented below in Table 6.

Table 6: Normal Gear Shift Table

Index	Low Symbol Rate (KHz)	High Symbol Rate (KHz)	Samples/ Symbol	Low Frequency (KHz)	High Frequency (KHz)
7	9.6	16	64	614.4	1024
6	16	32	32	512	1024
5	32	42	24	768	1008
4	43	64	16	672	1024
3	64	85	12	768	1020
2	85	238	8	680	1024
1	128	170	6	768	1020
0	170	256	4	680	1024

First, 128 samples are collected. At 4 samples per symbol, this is equivalent to 32 symbols. The first AGC acquisition is performed on the block of 128 samples (step 92). During this step, the following is calculated.

$$Ems = \frac{1}{N} \sum_{i=1}^N |Z_i|^2$$

where N = 128 samples at 4 samples per symbol and the AGC value is calculated utilizing the following equation:

$$AGC = \frac{Ems}{2 \times 16^2}$$

The next step is to perform timing acquisition (step 94). The following definitions apply:

'block of symbols': 16 contiguous symbols

- t_i : DFT estimate of a block of symbols, $i = 1..N$
N: number of DFT estimates
'group of DFT estimates': group of N DFT estimates
 T_i : average estimate of group of N DFT estimates
5 K: number of average estimates T_i , which is the number of points used as input to the Least Squares Fit

The timing acquisition is performed utilizing the following pseudo code.

In connection with the following Pseudo Code, the following assumptions are made.

- 10 (1) blocks of 16 contiguous symbols at 4 samples per symbol are available, i.e., $16 * 4 = 64$ continuous samples; (2) the next block of 16 symbols arrive after a break of $16 * 3 = 48$ symbols; and (3) the maximum drift between the receiver and the transmitter clocks is approximately 100 ppm.

- The method of the invention utilizes the timing recovery technique described in M.
15 Oerder and H.Meyr, "Digital Filter and Square Timing Recovery," IEEE Transactions on Communications, Vol. COM-36, pages 605 to 612, May 1988, incorporated herein by reference. The method of the invention is given briefly below.

1. Perform steps 2 through 5 for K groups made up of N DFT estimates, each calculated from blocks of 16 symbols.
- 20 2. Calculate timing estimate t_i , based on the DFT technique for 16 contiguous symbols, $i = 1..N$, thereby obtaining N DFT estimates each based on 16 symbols.
3. Make a histogram (3 bins in the range of -0.5, 0.5) of the N DFT estimates t_i obtained in step 2.
4. Classify the timing range (0, $\frac{1}{4}$, $\frac{1}{2}$, $-\frac{1}{4}$) the group the N estimates are in. The
25 decision is derived from logic based on the histogram in step 3.
5. Unwrap N DFT estimates based on a range decision derived from logic and calculate their average T_i .
6. Unwrap the K average estimates T_i and do a least square fit to the K averages to produce the final estimate.

30

Timing Acquisition Pseudo Code (in more detail)

1. for $k = 1$ to K perform steps 2 through 5 inclusive)groups of average estimates T_i ;
2. calculate the timing estimate t_i based on a DFT algorithm for 16 contiguous
35 symbols, $i = 1..N$, thereby obtaining N DFT estimates each based on 16 symbols contiguous at 4 samples per symbol with no discontinuity in time.

for $i = 1$ to N

$$e_r = \sum_{j=1}^{16} \left\{ \log[1 + SNR \cdot |z(4j+0+16 \cdot 4 \cdot (i-1))|^2] - \log[1 + SNR \cdot |z(4j+2+16 \cdot 4 \cdot (i-1))|^2] \right\}$$

$$e_i = \sum_{j=1}^{16} \left\{ -\log[1 + SNR \cdot |z(4j+1+16 \cdot 4 \cdot (i-1))|^2] + \log[1 + SNR \cdot |z(4j+3+16 \cdot 4 \cdot (i-1))|^2] \right\}$$

endfor (i = 1 to N)

where

$$SNR = \frac{E_s}{N_o}$$

5 and E_s represents energy per symbol.

The preliminary estimate is then given by the following

$$t_i = \frac{1}{2 \cdot pi} \arctan\left(\frac{e_i}{e_r}\right) \quad i = 1..N \quad \text{DFT estimates}$$

Note that the arctan function can be approximated using the least squares method and the logarithm is the natural logarithm to the base 'e'.

10 3. construct a histogram of the N DFT estimates t_i wherein 3 bins in the range -0.5 to 0.5.

3.1 count the number of estimates t_i in each bin as defined by

bin 1 = [-0.5, -1/6]

bin 2 = [-1/6, 1/6]

15 bin 3 = [1/6, 0.5]

3.2 sort counts of the three bins in descending order and save their respective indices as follows:

max = value of the maximum count

20 mid = value of the middle count

min = value of the minimum count

I_{\max} = index of the bin with the maximum count

I_{mid} = index of the bin with the middle count

25 I_{\min} = index of the bin with the minimum count

4. classify the portion of the timing range the group of N estimates are in;

range 1 = around zero, i.e., [-1/8, 1/8]

30 range 2 = around 1/4, i.e., [1/8, 3/8]

range 3 = around 1/2 or -1/2, i.e., [-1/2, 3/8] and [3/8, 1/2]

range 4 = around -1/4, i.e., [3/8, -1/8]

if (max ≥ 10) & (mid + min ≤ 6) then

35 if $I_{\max} = 2$ then

range = 1; time round 0

elseif $I_{\max} = 1$

range = 4; time negative

else

6.1 unwrapping the K average estimates

The first step is to unwrap the K average estimates and receive new values T_i for $i = -\frac{K-1}{2}, \dots, \frac{K+1}{2}$ for odd K.

Unwrapping Pseudo Code

1. Detect positive and negative jumps in timing that are larger than 0.5. A positive jump is detected if

$$T(jp+1) - T(jp) > 0.5$$

A negative jump is detected if

$$T(jn+1) - T(jn) < 0.5$$

where $T(j)$ are the time estimates and j is the time index.

2. For positive jumps at index jp , subtract 1 from all subsequent time estimates (with indices $\geq jp$).

3. For negative jumps at index jn , add 1 to all subsequent time estimates (with indices $\geq jn$).

6.2 Calculate estimates of the slope a and the average b of the T_i , $i = 1$ to K , using a least square fit estimation

The estimate is calculated to be:

$$T = \frac{a \cdot (K-1)}{2} + b$$

with no prediction, or

$$T = a \cdot \left[\frac{(K-1)}{2} + p \right] + b$$

with a prediction of $p=1/2$ or $p=1$.

Where b and a are calculated by a least square fit to a linear curve given by

$$\hat{b} = \frac{1}{N} \sum_{i=-(K-1)/2}^{(K-1)/2} T_{i+(K-1)/2+1}$$

and

$$\hat{a} = \frac{\sum_{i=-(K-1)/2}^{(K-1)/2} i \cdot T_{i+(K-1)/2+1}}{\sum_{i=-(K-1)/2}^{(K-1)/2} i^2}$$

for odd K. The indices are chosen so that the first T_i generated is multiplied by $-(K-1)/2$.

With reference to Figure 9, once the timing has been acquired, the next step is to apply a matched filter (step 96). The matched filter is applied using 1 sample per symbol at the filter output with no phase rotation. The next step is a second AGC acquisition on a block of 128 samples at 1 sample per symbol (step 98).

- 5 At 1 sample per symbol, 32 samples are collected. The second AGC acquisition is performed on the block of 32 samples. During this step, the following is calculated,

$$Ems = \frac{1}{N} \sum_{i=1}^N |z_i|^2$$

where N = 128 samples at 4 samples per symbol and the AGC value is calculated utilizing the following equation:

10
$$AGC = \frac{Ems}{2 \times 16^2}$$

- The next step is to perform fine frequency estimation (step 100). The fine frequency estimation is performed on the output of the matched filter after timing acquisition has been performed. Note that in order to increase performance at low SNRs, preferably two periodograms are averaged rather than using only one. A flow diagram illustrating the fine frequency estimation processing portion of the variable rate modem is shown in Figure 10.

The following definitions apply:

NFFT: the number of bins in the FFT, 256 for high SNR and 1024 for low SNR

- 20 PADD: zero padding fraction, 0 for high SNR and 0.5 for low SNR

With reference to Figure 10, the timing acquisition is performed utilizing the following pseudo code.

Fine Frequency Acquisition Pseudo Code

- 25 1. for i = 0 to NFFT*PADD - 1
collect the output of the matched filter (step 110) $z_i = I_i + jQ_i$ at the correct time epoch (step 112);
do $z_i = z_i^4$ in two stages:
- 30 calculate $z_i^2 = u_i + jw_i$, where $u_i = I_i^2 - Q_i^2$, $w_i = 2I_iQ_i$
calculate $z_i^4 = x_i + jy_i$, where $x_i = u_i^2 - w_i^2$, $y_i = 2u_iw_i$
2. calculate a NFFT point of $\{z^4$ with NFFT*PADD zeros padded (step 114). The absolute value of the FFT squared is denoted by ES.

- 35 FFT shift ES:

$$ES'(i) = \begin{cases} ES\left(i - \frac{NFFT}{2}\right), i = \frac{NFFT}{2} + NFFT - 1 \\ ES\left(i + \frac{NFFT}{2}\right), i = 0 + \frac{NFFT}{2} - 1 \end{cases}$$

where ES' is the FFT shifted version of ES . From here on in, ES' is denoted by ES .

3. find the maximum of $\{ES_i\}_{i=0}^{NFFT-1}$ (step 116);

4. find the index of the peak denoted by $peak_index$;

5 the frequency estimation (step 118) is given as

$$\frac{1}{4} \cdot \frac{symbol_rate}{NFFT} \cdot \left(peak_index - \frac{NFFT}{2} \right)$$

6. alternatively, better results can be achieved if the modulation wipe off is performed as follows

$$(I_i^2 + Q_i^2) \exp\left(4j \arctan\left(\frac{Q_i}{I_i}\right)\right) = \frac{(Q_i - jI_i)^4}{I_i^2 + Q_i^2} = \frac{(I_i - jQ_i)^4}{I_i^2 + Q_i^2}$$

10 7. an approximation of the modulation wipe off can be achieved using the following:

$$7.1 \nu = \lfloor \log_2(I_i^2 + Q_i^2) \rfloor$$

This can be performed using iterated comparisons. The iteration is through the values $-3 \leq \nu \leq 4$.

15 7.2 The wipe off is performed by

$$\frac{(Q_i - jI_i)^4}{2^\nu}$$

20 With reference to Figure 9, the next step is to perform phase acquisition (step 102). The input to the phase acquisition portion of the method is Z_n which are complex samples (I and Q) at a rate of 1 sample per second. The value of N is equal to 16 complex samples. One assumption made is that the frequency offsets are smaller than $\frac{1}{8 \cdot N \cdot T}$ where T is the symbol period, i.e., for $N = 16$, less than $1/128$ of the symbol rate that is approximately the maximum frequency error.

25 The phase acquisition process receives N complex samples ($N = 16$) and functions to determine the rotation angle that brings the samples after modulation wiping to a minimum variance. I and Q are the in phase and quadrature components, respectively.

$$z_n = I_n + jQ_n, n = 0..N-1$$

30 The method consists of two stages: (1) a coarse grained search that chooses between 4 'hypothesis' of signal rotation with modulation unwiping in the first quadrant and (2) a fine estimation of the phase rotation angle. The role of the operation z' is to wipe off the effect of

'normalize' X to the range of [0.5..1] which can be performed using left shift operations as follows

$$\bar{x} = 2^n \cdot x$$

$$u = 4.2349\bar{x}^2 - 5.8354\bar{x} + 2.6192$$

2.2.2 calculate

$$5 \quad v = \frac{y}{x} = 2^{-n} \cdot (y, u)$$

137); where the 'unnormalization' by a factor of 2^m is performed using right shifts (step

2.2.3 calculate $\alpha = \text{atan}(v)$ using a quadratic fit (step 138):

$$\alpha = -0.0052v^2 + 1.0804v - 0.2886$$

10 **Note:** (1) these coefficients are scaled in radians;

(2) this approximation assumes that $0 < v < 1$ which is true because $v = x/y$ and 2.1 assures that $x > y$;

2.2.4 if the *swap_flag* is set (step 139) then $\alpha = 90^\circ - \alpha$ (step 140);

2.3 the rotation angle Θ , which must be subtracted from the phase of the samples z_n , is
 15 given as

$$\odot = \odot_k + \alpha - 45^\circ \text{ (step 142)}$$

2.4 the rotation by Θ yields

$$z_n = z_1 e^{-j\theta}$$

20. This rotation operation brings in the received signal at phase $\pm \pi/4, \pm 3\pi/4$, etc. in accordance with the data (for noiseless signals). Note that steps 132 through 140 comprise the detail implementation of step 130.

The rotation angle Θ obtained during acquisition is the initial phase of the phase control loop.

25 A block diagram illustrating pre-tracking and tracking portion of the variable rate modem is shown in Figure 13. This block diagram describes both the pre-tracking and tracking stages of the main loop processing. The I and Q data output from the matched filter is input to a mixer (multiplier) 211. The I and Q output of the mixer 211 is input to AGC estimation 213, timing detector 214 and phase detector 215.

30 The AGC estimation 213 functions to generate an AGC control based on the energy or average power of the input signal. The AGC control is passed through a loop filter 216 before being applied to the AGC hardware in the IF module section 16 (Figure 1).

The timing detector 214 functions to generate a noisy timing estimate which is first filtered via loop filter 217 before being applied to the clock generation circuitry (not shown) in the A/D converter section of the baseband module 18. The A/D clock control signal output

from the loop filter 217 functions to adjust and correct for clock timing errors in the A/D converters.

The phase detector 215 functions to generate a noisy phase estimate that is input to the loop filter 218. One signal output of the loop filter comprises a VCO control signal which is input to the VCO circuitry (not shown) in the IF module 16. The VCO control signal functions to raise or lower the frequency output of the VCO. A second signal output of the loop filter 218 is the phase estimate $\hat{\phi}$ that is fed into the $e^{j\phi}$ block 212. This block functions to correct for phase and small frequency offsets. The output of the block constitutes the second input to the I/Q mixer 211.

The I and Q output of the mixer 211 is also input to the soft decision block 219. The matched filter outputs z_n , after time synchronization, frequency and phase correction, must pass the soft decision block 219 before being input to Viterbi detection in the Viterbi decoder (not shown) in the baseband module 18 (Figure 1) (see also step 158 Figure 14). This process is performed on I_n and Q_n independently. The Viterbi decoder receives for each I_n and Q_n , 3 or 4 bits of quantization. The exact number depends on the specific Viterbi detector. One of the bits is the sign and the other bits describe the signal level.

For example, if the level thresholds are $\alpha_1 < \alpha_2 < \alpha_3$, the two bits of soft decision which describe the level are shown below in Table 7:

Table 7

I_n	Bit Representation
$I_n < \alpha_1$	00
$\alpha_1 < I_n < \alpha_2$	01
$\alpha_2 < I_n < \alpha_3$	10
$\alpha_3 < I_n$	11

With reference to Figure 3, once the acquisition stage is complete, pre-tracking can be performed (step 37). The pre-track stage is in principle normal tracking of AGC and timing, while the phase tracking loop has a larger bandwidth and the 90° ambiguity still must be resolved. A flow diagram illustrating the pre-track processing portion of the variable rate modem is shown in Figure 14.

The method comprises (1) AGC tracking as described hereinabove, (2) timing tracking using a method that operates on a group of symbols (at one sample per symbol) to generate an estimate that is filtered using a single pole IIR filter; the method is called at a rate of approximately 160 Hz which 32 symbols being processed each time, and (3) phase

tracking performed once per symbol for symbol rates below 64 KHz and once every 2 or 4 symbols for higher symbol rates. The criteria for declaring tracking lock can be a timeout, a high raw BER or one or more lock detectors.

First, the I and Q data is input to the matched filter (step 150). AGC tracking is then performed on the output of the matched filter (step 152). A flow diagram illustrating the AGC tracking portion of the variable rate modem is shown in Figure 15. The pseudo code for the AGC tracking follows.

AGC Tracking Pseudo Code

1. initialize variables including 'count' and set the threshold to 256 (step 180);
2. check if count = 8 (step 182);
3. every T milliseconds ($T \approx 100$ ms) receive the output z_n (n represents one sample per symbol) of the matched filter (step 186) while count is < 8;
4. calculate g_n as follows (step 196)

$$g_n = \text{Threshold} \cdot |z_n|^2$$

5. calculate AGC value (step 198). Filter g_n using a Butterworth low pass filter (LPF) transfer function shown below

$$H(z) = \frac{0.073 \cdot (1 + z^{-1})}{1 - 0.854 \cdot z^{-1}}$$

- with a 3dB cutoff rate at 0.1 of the digital Butterworth LPF. The corresponding difference equation is as follows

$$G_{n+1} = 0.854 \cdot G_n + 0.073 \cdot (g_n + g_{n-1})$$

6. the output Y_n of this filter is the new 'inverse AGC' (in the energy domain) (step 200).

$$AGC = \frac{1}{G_n}$$

7. to prevent clipping at the input to the A/D converter, the threshold is adapted every $K \cdot T$ ms ($K \approx 8, 16$).

8. find Y_n in an *inverse_AGC_table* and write the value to the AGC circuitry in the IF module;

8. increment count by one;

9. after N samples ($N = 8$ in the above example) reset count to 0 and calculate Ems (step 184);

$$Ems = \frac{1}{N} \sum_{i=1}^N |Z_i|^2$$

10. if $Ems > 0.25$ (step 188) then increase the *threshold* (step 192);

$$\text{Threshold} = \alpha \cdot \text{Threshold}, \quad \alpha \approx 1 + 1/8$$

- else if the *threshold* > 1/256 AND $Ems < 0.24$ (step 190) then decrease *threshold* (step 194);

$$\text{Threshold} = \beta \cdot \text{Threshold}, \quad \beta \approx 1 - 1/32$$

endif

With reference to Figure 14, the next step is to perform timing tracking (step 154). The timing tracking portion comprises a loop filter, an ideal integrator and an inherent numerically controlled oscillator (NCO). A block diagram illustrating a physical model of the timing tracking portion of the variable rate modem is shown in Figure 16. The filtered I and Q data at 1 sample per symbol, i.e., the output of the mixer 211 (Figure 13), is input to a Mueller error detector 170. The output of the error detector 170 is input to a loop filter 172. The output of the filter constitutes the A/D clock control signal. This signal is input to NCO 174 that functions to generate the clock for the A/D converter. The output of the NCO is also fed back to the Mueller error detector 170.

The timing signal model of the loop filter 172 can be represented as the following

$$\beta \frac{1 - \gamma z^{-1}}{1 - z^{-1}}$$

and the NCO can be represented as

$$\frac{1}{1 - z^{-1}}$$

Note that the loop filter has a gain of β , an ideal integrator and a zero at γ , i.e., proportional and derivative control. The timing tracking loop utilizes the Mueller and Mueller timing error detector 170 which operates on the filtered in-phase and quadrature components on a block of 32 symbols at a rate of approximately 320 Hz (determined by the operating system). The timing error detector is given by the average of the I and Q error components:

$$\epsilon_n = \frac{\epsilon_I + \epsilon_Q}{2K}$$

where

$$\epsilon_{In} = I_n \cdot \text{sgn}(I_{n-1}) - I_{n-1} \cdot \text{sgn}(I_n)$$

$$\epsilon_{Qn} = Q_n \cdot \text{sgn}(Q_{n-1}) - Q_{n-1} \cdot \text{sgn}(Q_n)$$

and $K \approx 1/16$ is the nominal value of the signal amplitude as set by the AGC. Next, the average of a block size $N = 32$ is computed as follows:

$$E_n = \frac{1}{N} \sum_{i=0}^{N-1} \epsilon_{n-i}$$

The error process is filtered by the loop filter 172 as follows:

$$t_n = t_{n-1} + \beta(E_n - \gamma E_{n-1})$$

where t_n is the correction written to the hardware. The NCO 174 or ideal integrator is part of the system and may or may not be implemented in software. It should, however, be taken into account when calculating the closed loop transfer function. Based on the timing signal model given above and the assumption that the error detector is ideal, i.e., it yields the exact timing error), the closed loop transfer function of the estimated timing epoch is given by

$$\frac{\hat{T}}{T} = \frac{\beta(1 - \gamma z^{-1})}{1 + (\beta - 2)z^{-1} + (1 - \beta\gamma)z^{-2}}$$

Note that it is convenient to construct the filter using the classical parameters from continuous time in terms of $\omega_n = 2\pi f_n$, the natural frequency and ξ , the damping factor. it is desirable to express β and γ in terms of ω_n and ξ . This can be achieved in two stages. The first stage is to convert to the discrete time domain standard form by solving the following set of equations:

$$\begin{cases} (\beta - 2)z^{-1} = -2r \cos \theta z^{-1} \\ (1 - \beta\gamma)z^{-2} = r^2 z^{-2} \end{cases}$$

from which we obtain

$$\begin{cases} r = \sqrt{1 - \beta\gamma} \\ \theta = \cos^{-1}\left(\frac{2 - \beta}{2r}\right) \end{cases}$$

or for the other direction

$$\begin{cases} \beta = 2(1 - r \cos \theta) \\ \gamma = \frac{1 - r^2}{\beta} = \frac{1 - r^2}{2(1 - r \cos \theta)} \end{cases}$$

We now express r and θ in terms of the design parameters ω_n and ξ as follows.

$$\begin{cases} r = e^{-\xi\omega_n T} \\ \theta = \omega_n T \sqrt{1 - \xi^2} \end{cases}$$

This is described in more detail in Best, Phased Locked Loops, Second Edition, p. 342, McGraw Hill, 1993. In addition, a more detailed description of the timing error detector 170 is given in IEEE Transactions on Communications, May 1976, pp. 516 to 530.

The following is based on the assumption that the timing error detector gain is unity. The detector gain will now be discussed in more detail. The transformation is based on the impulse invariance conversion from continuous to discrete time. From r and θ we can

compute β and γ . Based on the above equations, assuming an operating rate of $1/T = 320$ or 640 operations per second and setting $\xi = 0.707$, the parameters for β and γ are presented below.

Table 8: Parameters β and γ

f_n (Hz) @ 320 Hz	β	γ	f_n (Hz) @ 640 Hz
0.1	0.0028	0.9986	0.2
0.2	0.0056	0.9972	0.4
0.32	0.0089	0.9956	0.64
0.5	0.0139	0.9931	1
1	0.0278	0.9863	2
1.6	0.0444	0.9783	3.2
2	0.0555	0.9730	4
3.2	0.0888	0.9575	6.4
5	0.1386	0.9351	10
7.5	0.2075	0.9058	15
10	0.2760	0.8784	20

The choice of $\xi = 0.707$ is due to the dependence of the gain on the error detector which is a function of the AGC and the signal to noise ratio.

With reference to Figure 14, the next step after timing tracking is phase tracking (step 156). A block diagram illustrating the phase tracking portion of the variable rate modem is shown in Figure 17. The phase tracking comprises three main components including a phase detector 254, loop filter 258 and a frequency jump 262 if the frequency is larger than a threshold.

The phase tracker mainly operates at the symbol rate. For higher data rates, real time constraints may pose a problem. For high symbol rates it may be necessary to operate the phase tracking at rates slower than the symbol rate.

The filtered I and Q data is input to a mixer 252. The output of the mixer 254 is input to the phase detector 254. The QPSK phase detector performs the following:

$$\epsilon_n = Q_n \cdot \text{sgn}(I_n) - I_n \cdot \text{sgn}(Q_n)$$

where I and Q denote in-phase and quadrature components, respectively, at a rate of once per symbol.

The output of the phase detector is input to a loop filter 258. The filter is presented in state space representation. The filter is defined by the parameters a_0 and a_1 . The Doppler estimate, D_n , is preferably also input to the filter from an external loop. The equations are shown below wherein F_n and P_n denote the frequency and phase, respectively. Note that the

phase P_n is the same phase discussed earlier denoted $\hat{\phi}$ or Θ . The filter preferably comprises an infinite impulse response (IIR) filter. The loop filter performs the following:

$$\begin{aligned} F_{n+1} &= a_1(P_n - P_{n-1}) + b_1 F_n + D_n \\ P_{n+1} &= b_0 \varepsilon_n + P_n + F_{n+1} - D_n \end{aligned}$$

where ε_n is the phase error from the phase detector and $a_1 = 1 - b_1$.

- 5 If the frequency F_n in the filter is large, a jump in the direct digital synthesizer (DDS) or other similar frequency source is performed having a size Δf . A typical value of Δf corresponds to 10 Hz.

The absolute value of the output of the loop filter F_{n+1} is compared against a threshold via a compare block 260 that performs the following comparison:

10 $|F_{n+1}| > \frac{\Delta f}{2}$

If the expression is true then jump Δf in the opposite direction via frequency jump 262. Note that the F_n and threshold values are in units of Radians/operating period.

The data is written to the direct digital synthesizer (DDS) using frequency jump unit 262 in accordance with the following

15 $synthesizer_freq = synthesizer_freq + \Delta f$

Note that the quantity Δf is in units of Radians/operating period.

The following variables apply:

$$\begin{aligned} P_n &= P_n - \frac{\Delta f}{2} \cdot \text{sgn}(F_n) \\ F_n &= F_n - \Delta f \cdot \text{sgn}(F_n) \end{aligned}$$

- 20 It is assumed that the Doppler variable is zero. For a non-zero Doppler value one skilled in the art can modify the above equations to include the Doppler variable.

Note also that the Doppler estimates are supplied from an external loop uncoupled to the IIR filter.

The output of the frequency jump 262 and the compare 260 are input to the $e^{j(\cdot)}$ block 264. The output of block 264 forms the second input of the mixer 252.

- 25 The transfer function of the IIR used in the loop filter 258 will now be described in more detail. by taking the Z transform of the two IIR equations (F_{n+1} , P_{n+1}) and substituting

$$\varepsilon_n = \phi_n - P_n$$

where ϕ_n is the phase of the input signal (linear approximation), we obtain:

$$\frac{\phi_n}{P_n} = \frac{b_0(1 - b_1 z^{-1})}{1 - (1 + a_0)z^{-1} + (a_0 b_1 + a_1)z^{-2}}$$

Note that it is convenient to use the normalized form for a second order system, i.e., to define the system by $\xi = 1$ or $\frac{\sqrt{2}}{2}$ and ω_n which is determined by the required lock range, Doppler offset or output signal to noise ratio (SNR). A damping coefficient of $\xi = 1$ is recommended for reducing cycle slips as described in Ascheid and Meyr, "Cycle Clips in PLLs: A Tutorial Survey," IEEE Transactions in Communications, Vol. 30, October 1982, pp. 2228 to 2241. For acquisition it is preferable to use a smaller damping coefficient in the range $\xi = 0.5$ to $\frac{\sqrt{2}}{2}$ which yields a faster response with an overshoot of 18% for $\xi = 0.5$.

After phase tracking is accomplished, the I and Q soft decisions are output to the Viterbi decoder (not shown) (step 158). Whether signal lock has been achieved is then determined by comparing the BER to a predetermined threshold (step 160). If lock has been achieved, the main tracking loop is entered. If it is determined that lock has not been achieved then the system goes back to the acquisition (step 161).

A flow diagram illustrating the tracking processing portion of the variable rate modem is shown in Figure 18. The various functions performed in tracking are substantially the same as those performed during the pre-tracking stage except for the phase tracking which has a smaller loop bandwidth.

The tracking stage comprises the steps of performing a matched filter (step 220), AGC tracking (step 222), timing tracking (step 224), phase tracking (step 226), I and Q soft decisions (step 228) and determining whether lock has been achieved (step 230). If it is determined that lock is achieved, the signal detection is declared (step 232).

In operation, the main loop advances from stage to stage until tracking is achieved. At that point, the BER is measured by the Viterbi decoder. If the BER indicates failure, then the system returns back to acquisition.

If the BER indicates lock, then the system remains in tracking until the BER indicates that the system is not in lock due to a large number of errors. Other indications may be used such as the behavior of phase locking loops.

While the invention has been described with respect to a limited number of embodiments, it will be appreciated that many variations, modifications and other applications of the invention may be made.

What is claimed is:

1. A satellite modem, comprising
a housing;
a antenna for receiving and transmitting radio frequency (RF) signals;
5 an upconverter/downconverter coupled to said antenna and adapted to upconvert RF signals from a first frequency band to a second frequency band, and adapted to downconvert RF signals from said second frequency band to said first frequency band;
an RF transceiver coupled to said upconverter/downconverter and adapted to receive
10 an output transmit signal and to generate an output RF signal therefrom, said RF transceiver adapted to receive an input RF signal from said upconverter/downconverter and generate an input receive signal therefrom;
an intermediate frequency (IF) module adapted to receive said input receive signal and generate I and Q signals in response thereto;
15 a baseband module adapted to receive said I and Q signals and to generate receive data in accordance therewith; and
a baseband module adapted to generate said output transmit signal in accordance with a transmit data signal input thereto.
2. A receiver baseband apparatus, comprising:
20 input means adapted to receive an I and Q signal;
a first matched filter adapted to receive said I signal and generate an I filtered output therefrom;
a second matched filter adapted to receive said Q signal and generate a Q filtered output therefrom;
25 a processor programmed to perform the steps of:
detecting the presence of signal activity as input to said receiver baseband apparatus;
acquiring said signal once it is detected;
pre-tracking said signal once it is detected;
30 tracking said signal once it is detected;
a decoder adapted to receive said I output signal and said Q output signal from said processor and to generate a decoded output therefrom;

a deinterleaver adapted to generate a deinterleaved output in accordance with said decoded output signal input thereto;

a forward error correction decoder adapted to generate output receive data in accordance with said deinterleaved output signal input thereto; and

5 a controller adapted to manage and control said input means, first matched filter, second matched filter, said processor, said decoder, said deinterleaver and said forward error correction decoder.

3. The apparatus according to claim 2, wherein said step of detecting the presence of signal activity comprises the steps of:

10 performing initial automatic gain control (AGC) on said signal;
performing signal decimation; and
performing signal detection and frequency acquisition.

4. The apparatus according to claim 2, wherein said step of acquiring said signal comprises the steps of:

15 inputting said signal to a first matched filter;
performing a first automatic gain control (AGC) acquisition;
performing timing acquisition;
inputting said signal to a second matched filter;
performing a second automatic gain control (AGC) acquisition;
20 performing fine frequency estimation; and
performing phase acquisition.

5. The apparatus according to claim 2, wherein said step of acquiring said signal comprises the step of performing coarse phase acquisition on said signal, wherein said step of performing coarse phase acquisition comprises the steps of:

25 rotating vectors z_n representing said signal into a single quadrant by an angle Θ_k ;
wiping off said $z_n(\Theta_k)$ modulation;
summing the wiped off vectors $z_n(\Theta_k)$;
determining the energy contained within a plurality of hypotheses; and
selecting a single hypothesis from said plurality of hypotheses having the maximum
30 energy.

6. The apparatus according to claim 2, wherein said step of pre-tracking comprises the steps of:

inputting said signal to a matched filter;

performing automatic gain control (AGC) tracking;

5 performing timing tracking;

performing phase tracking;

generating I and Q soft decisions; and

determining whether signal lock has been achieved.

7. The apparatus according to claim 2, wherein said step of pre-tracking comprises the steps of performing timing acquisition on K groups, each made up of N DFT estimates, each estimate calculated from blocks of 16 symbols, said step of performing timing acquisition comprising the steps of:

calculating a timing estimate t_i based on a DFT for 16 contiguous symbols, $i = 1, \dots, N$,

thereby obtaining N DFT estimates each based on a block of symbols;

15 generating a histogram of said N DFT estimates t_i ;

classifying a timing range said group the N estimates are in based on said histogram;

unwrapping said N DFT estimates and calculating their average T_i ; and

unwrapping K average estimates T_i and performing a least square fit of said K averages so as to generate a final estimate.

20 8. The apparatus according to claim 1, wherein said decoder comprises a Viterbi decoder.

9. The apparatus according to claim 1, wherein said upconverter/downconverter is adapted to upconvert an L band signal to a C or Ku band signal.

10. The apparatus according to claim 1, wherein said upconverter/downconverter is
25 adapted to downconvert a C or Ku band signal to an L band signal.

11. A receiver baseband apparatus, comprising:

input means adapted to receive an I and Q signal:

an I matched filter adapted to receive said I signal and generate an I filtered output therefrom;

30 a Q matched filter adapted to receive said Q signal and generate a Q filtered output therefrom;

a processor programmed to:

perform automatic gain control (AGC) and generate an AG control signal therefrom;

perform timing detection and generate an A/D clock control signal therefrom;

5 perform phase detection and generate a voltage controlled oscillator (VCO) control signal therefrom;

a decoder adapted to receive said I output signal and said Q output signal from said processor and to generate a decoded output therefrom;

10 a deinterleaver adapted to generate a deinterleaved output in accordance with said decoded output signal input thereto;

a forward error correction decoder adapted to generate output receive data in accordance with said deinterleaved output signal input thereto; and

15 a controller adapted to manage and control said input means, I matched filter, Q matched filter, said processor, said decoder, said deinterleaver and said forward error correction decoder.

12. The apparatus according to claim 11, wherein said step of detecting the presence of signal activity comprises the steps of:

performing initial automatic gain control (AGC) on said signal;

performing signal decimation; and

20 performing signal detection and frequency acquisition.

13. The apparatus according to claim 11, wherein said step of acquiring said signal comprises the steps of:

inputting said signal to a first matched filter;

performing a first automatic gain control (AGC) acquisition;

25 performing timing acquisition;

inputting said signal to a second matched filter;

performing a second automatic gain control (AGC) acquisition;

performing fine frequency estimation; and

performing phase acquisition.

30 14. The apparatus according to claim 11, wherein said step of acquiring said signal comprises the step of performing coarse phase acquisition on said signal, wherein said step of performing coarse phase acquisition comprises the steps of:

rotating vectors z_n representing said signal into a single quadrant by an angle Θ_k ;
wiping off said $z_n(\Theta_k)$ modulation;
summing the wiped off vectors $z_n(\Theta_k)$;
determining the energy contained within a plurality of hypotheses; and
5 selecting a single hypothesis from said plurality of hypotheses having the maximum
energy.

15. The apparatus according to claim 11, wherein said step of pre-tracking comprises the
steps of:

inputting said signal to a matched filter;
10 performing automatic gain control (AGC) tracking;
performing timing tracking;
performing phase tracking;
generating I and Q soft decisions; and
determining whether signal lock has been achieved.

15 16. The apparatus according to claim 11, wherein said step of pre-tracking comprises the
steps of performing timing acquisition on K groups, each made up of N DFT estimates, each
estimate calculated from blocks of 16 symbols, said step of performing timing acquisition
comprising the steps of:

calculating a timing estimate t_i based on a DFT for 16 contiguous symbols, $i = 1, \dots, N$,
20 thereby obtaining N DFT estimates each based on a block of symbols;
generating a histogram of said N DFT estimates t_i ;
classifying a timing range said group the N estimates are in based on said histogram;
unwrapping said N DFT estimates and calculating their average T_i ; and
unwrapping K average estimates T_i and performing a least square fit of said K
25 averages so as to generate a final estimate.

ABSTRACT

A satellite modem whose baseband modules can be implemented mostly in software running on a suitable processor such as a high speed digital signal processor (DSP). The modem includes a RF portion and a baseband portion. The digitized output of a matched
5 filter is input to the baseband processing portion that consists of software executing on a DSP. The modem comprises an antenna coupled to an upconverter/downconverter. The upconverter/downconverter is coupled to a RF transceiver which functions to receive a transmit signal from a baseband transmitter module and generate a signal for input to the upconverter/downconverter. The RF transceiver also functions to receive a downconverted
10 signal and output an IF signal for input to an IF module. The IF functions to generate I and Q outputs that are input to a digital baseband module. The baseband module can be implemented as software executing on a DSP. Also included in a technique of modulation wipe off wherein the effects of modulation are removed. A signal detection technique performs signal detection and frequency acquisition in the presence of multiple signals in
15 accordance with a method described hereinbelow. A timing acquisition technique includes an unwrapping technique that functions to correct timing errors before averaging is performed. Linear changes to the time estimates are performed using LSR techniques.




FIG.1






FIG.2

[illegible]

INITIAL
AGC




FIG.5




FIG. 6




FIG. 7

FIG.8




FIG.9


```

graph TD
    A([FINE FREQUENCY ESTIMATION]) --> B[COLLECT OUT OF MATCHED FILTER 110]
    B --> C[CALCULATE  $Z_i$  112]
    C --> D[CALCULATE SPECTRUM ESTIMATE 114]
    D --> E[DETERMINE PEAK 116]
    E --> F[ESTIMATE FREQUENCY 118]
    F --> G([END])
  
```

FIG. 10





FIG.11






FIG. 13


```

graph TD
    Start([AGC TRACKING]) --> Init[INITIALIZE 180]
    Init --> Count8{COUNT = 8 ? 182}
    Count8 -- YES --> Count0[COUNT = 0  
CALCULATE EMS 184]
    Count8 -- NO --> GetOutput[GET MATCHED  
FILTER OUTPUT 186]
    Count0 --> EmS{EMS > 0.25 ? 188}
    EmS -- YES --> Threshold1[THRESHOLD =  
1.125 * THRESHOLD 192]
    EmS -- NO --> Threshold2{THRESHOLD > 1/256  
AND  
EMS < 0.24 ? 190}
    Threshold1 --> CalcGn[CALCULATE Gn 196]
    Threshold2 -- YES --> Threshold3[THRESHOLD =  
0.968 * THRESHOLD 194]
    Threshold2 -- NO --> CalcGn
    CalcGn --> CalcAGC[CALCULATE AGC  
VALUE 198]
    CalcAGC --> CalcYn[CALCULATE Yn 200]
    CalcYn --> CountInc[COUNT =  
COUNT + 1 202]
    CountInc --> Count8

```

FIG.15




FIG. 16




FIG. 17

Figure 1 consists of two vertically stacked panels. The top panel shows the evolution of the electron-to-proton temperature ratio T_e/T_p (solid line) and the ionization fraction X_H (dashed line) as a function of redshift z . The y-axis is logarithmic, ranging from 10^{-4} to 10^0 . The x-axis is logarithmic, ranging from 10^{-2} to 10^0 . The bottom panel shows the evolution of the ionization fraction X_H from $z=10$ to $z=0$. The y-axis is logarithmic, ranging from 10^{-4} to 10^0 . The x-axis is logarithmic, ranging from 10^{-2} to 10^0 . The top panel also includes a shaded region representing the uncertainty in the ionization fraction.




FIG. 18

DECLARATION AND POWER OF ATTORNEY FOR PATENT APPLICATION

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below under my name.

I believe that I am the original, first and sole inventor of the subject matter which is claimed and for which a patent is sought on the invention entitled

VARIABLE RATE CONTINUOUS MODE SATELLITE MODEM

the Specification of which

is attached hereto

was filed on

as Application Serial No.

and was amended on _____ (if applicable).

I hereby state that I have reviewed and understand the contents of the above-identified Specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to the examination of this application in accordance with Title 37, Code of Federal Regulations, 1.56(a).

I hereby claim foreign priority benefits under Title 35, United States Code, §119 of any provisional application filed in the United States in accordance with 35 U.S.C. §1.119(e), or any application for patent that has been converted to a Provisional Application within one (1) year of its filing date, or any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed.

PRIOR FILED APPLICATION(S)

APPLICATION
NUMBER

COUNTRY

(DAY/MONTH/YEAR FILED)

PRIORITY
CLAIMED

I hereby claim the benefit under Title 35, United States Code, §120 of any United States application listed below, and, insofar as the subject matter of each of the claims of this application is not disclosed in any prior United States application in the manner provided by the first paragraph of Title 35, United States Code, §112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, §1.56(a), which occurred between the filing date of the prior application and the national or PCT international filing date of this application.

APPLICATION
NO.

FILING DATE
(DAY/MONTH/YEAR)

STATUS - PATENTED,
PENDING, ABANDONED

I hereby appoint as my attorney(s) and agent(s) Heidi M. Brun (Agent, Registration No. 35,104), or Jerome R. Smith, Jr. (Attorney, Registration No. 35,684), or Daniel J. Swirsky (Agent, Registration No. 45, 148) or Mark S. Cohen (Attorney, Registration No. 42, 425) said attorney(s) and agent(s) with full power of substitution and revocation to prosecute this application and transact all business in the Patent and Trademark Office connected therewith.

Please address all correspondence regarding this application to:

EITAN, PEARL, LATZER, & COHEN-ZEDEK
ONE CRYSTAL PARK, SUITE 210
2011 CRYSTAL DRIVE
ARLINGTON, VA 22202-3709

Direct all telephone calls to (703) 486-0600 and all facsimiles at (703) 486-0800.

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further, that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

FULL NAME OF INVENTOR: DAVIDSON, Jeffrey

FULL RESIDENCE ADDRESS: 2 Kar/com Street, Kochav Yair 44864, Israel

COUNTRY OF CITIZENSHIP: Israel

FULL POST OFFICE ADDRESS: same

SIGNATURE OF INVENTOR *J Davidson*

DATE X 18.4.00

FULL NAME OF INVENTOR: POKRASS, Alexander

FULL RESIDENCE ADDRESS: 14 Israel Ben Zion, Bat Yam 59572, Israel

COUNTRY OF CITIZENSHIP: Israel

FULL POST OFFICE ADDRESS: same

SIGNATURE OF INVENTOR

DATE

5.05.00

FULL NAME OF INVENTOR: GOLDENBERG, Sorin

FULL RESIDENCE ADDRESS: 27 Ben Yehuda Street, Petach Tikva 49373, Israel

COUNTRY OF CITIZENSHIP: Israel

FULL POST OFFICE ADDRESS: same

SIGNATURE OF INVENTOR

DATE

23. 4. 00

FULL NAME OF INVENTOR: WAYER, Israel Shahaf

FULL RESIDENCE ADDRESS: 30 Haneviim street, Tel Aviv 64072, Israel

COUNTRY OF CITIZENSHIP: Israel

FULL POST OFFICE ADDRESS: same

SIGNATURE OF INVENTOR

DATE

3/5/2000